

KENWOOD

SB-958

SERVICE BULLETIN AMATEUR RADIO

SUBJECT

MC-44DM MICROPHONE AUDIO IMPROVEMENTS

DATE

01/12/90

There are several ways to increase the transmit audio level when using an MC-44DM. If you are using a single band transceiver such as the TM-231A, you can turn up the deviation control inside the transceiver. Do not turn up the deviation controls in dual banders such as the TM-731A because the audio will distort during repeater cross band operations.

Inside the microphone, there is a felt pad lightly glued to the microphone element housing. Removing the pad will increase the audio level.

If more level is desired, the microphone element can be changed to a more sensitive element. The element can be ordered through Kenwood's Parts Department.

ECM (MICROPHONE ELEMENT) PART# T91-0393-08

This is an optional change that is not covered under warranty.
Time required to replace the ECM is 1 hour or less. (C)010390EWP

KENWOOD U.S.A. CORPORATION

2201 EAST DOMINGUEZ STREET - LONG BEACH, CALIFORNIA 90810
MAILING: P.O. BOX 22745 - LONG BEACH, CALIFORNIA 90801-5745
TELEPHONE: (213) 639-9000